



**BOX**<sup>SM</sup>  
TECHNOLOGY

**Network Connectivity**

**SOLA® Network Connection  
Specifications for BOX**

BOXM\_PRC\_SOLA® Network Connection Specifications\_v032

Document Revision: 3.2

Date of Issue : 2021-07-29

## Copyright

---

This document and all information contained herein is and will remain at all times proprietary and confidential information of BOX Technology.

No part of this document may be photocopied, reproduced, stored on retrieval system, or transmitted, in any form or by any means whether, electronic, mechanical, or otherwise without the prior written consent of BOX Technology.

The information included in this document is believed to be accurate. BOX Technology does not guarantee the completeness or accuracy of any information included herein. This document is produced with the understanding that BOX Technology is providing information and not in any way providing engineering or other professional services.

BOX Technology reserves the right to change details in this publication without notice.

## Document History

---

Version.	Date	Change Description
3.0	2019-07-05	New BOX version to replace previous TMX version with the following updates: <ul style="list-style-type: none"><li>• Removed outdated reference to rack space provided by BOX</li><li>• Updated bandwidth requirements</li></ul>
3.1	2020-10-02	Added multicast source IP information for NY4 multicast feeds
3.2	2021-07-29	Added information for 1Gbps multicast feed Updated ISV HSFV information to reflect new addresses

# Table of Contents

---

**Section 1 Introduction..... 3**  
**Section 2 Connectivity ..... 4**  
**Section 3 HSVF Multicast Specifications ..... 7**  
**Section 4 Point of Presence Sites..... 11**

## List of Tables

---

Table 1: Applications Available Through BOX .....	4
Table 2: HSVF Bandwidth Requirements.....	5
Table 3: HSVF Multicast Feeds.....	7
Table 4: VPN Connections Policies.....	12
Table 5: Rendezvous Point – Secaucus .....	14
Table 6: Multicast Sources – Secaucus .....	14
Table 7: IP Routing – Secaucus .....	14
Table 8: Multicast Lines – Secaucus .....	15
Table 9: Multicast line to source IP - Secaucus .....	18
Table 10: Retransmission Feeds – Secaucus.....	18
Table 11: Rendezvous Point – Chicago .....	19
Table 12: Multicast Sources – Chicago.....	19
Table 13: IP Routing – Chicago.....	20
Table 14: Multicast Lines – Chicago .....	20
Table 15: Retransmission Feeds – Chicago .....	22
Table 16: Rendezvous Point – Test Environment.....	23
Table 17: Multicast Sources – Test Environment.....	23
Table 18: IP Routing – Test Environment .....	24
Table 19: Multicast Lines – Test Environment .....	25
Table 20: Retransmission Feeds – Test Environment .....	27

## Section 1 Introduction

---

This **Network Connection Specifications** document outlines the specifications and requirements for clients to connect to the BOX Options Exchange (BOX) trading networks. This document was produced by BOX Technology.

### 1.1 Intended Audience

This document targets business, programmer, and network analysts who are responsible for determining the technical solutions needed to connect to the BOX market for order entry and market data feed access.

### 1.2 Scope

This document covers the following topics:

- Connectivity
- High Speed Vendor Feed (HSVF) multicast
- Points of Presence (POP) sites
- Routing information

### 1.3 Related Documents

- HSVF-BX-002E BOX SOLA HSVF Multicast Specifications Guide

### 1.4 BOX Contact

Market Operations Center Support / Technical Help Desk

Toll Free: 1-866-768- 8845

[boxmoc@boxoptions.com](mailto:boxmoc@boxoptions.com)

## Section 2 Connectivity

Clients can obtain access to the BOX test and production environments through separate production and test networks. Clients (Providers) will need to connect to one or both depending on their needs.

### 2.1 Applications

Main applications available through the BOX network are summarized in Table 1:

**Table 1: Applications Available Through BOX**

Service Name	Description
SAIL	The native gateway for order and quote entry on BOX.
FIX	The FIX gateway for order entry on BOX.
HSVF	BOX High Speed Vendor Feed: Outbound market data feed.
ATR	BOX Automated Trade Reporting (ATR) feed provides Participants with 'drop copies' of all their trades on BOX.
Reports	Various Participant reports available on BOX sftp server.

### 2.2 Production Access

To gain access to the BOX production trading services, clients must obtain a connection to the BOX production network. VPN connections to the production network **will not** be accepted. Access to the production network can be obtained by one of the following methods:

#### 2.2.1 Direct Connect

A direct connection can be made to one or more of the BOX POP sites. A list of the POP sites is available in [Section 4](#).

##### Network Connectivity

Physical connection to the BOX production network is provided by an Ethernet connection (gigabit or 10 gigabit).

##### Redundancy

BOX can accept multiple connections for redundancy. At each location, BOX has redundant equipment and can therefore provide diverse connections to the BOX production network. For added redundancy, a client may also install redundant links to different POP sites.

### 2.2.2 Third Party Networks

A 3rd Party Network Provider is a party who provides a shared access to the BOX production network through a single (redundant) network connection.

For a list of 3rd Party Network Providers offering connectivity to BOX, please visit our website at <http://boxexchange.com/technology/connectivity>.

## 2.3 Test Access

Access to the BOX test environment can be obtained using the following connectivity options:

- Production Extranet: Participants may choose to access the test environment over their production cross connect
- Test Extranet: Participants may choose to obtain a dedicated cross connect to the test network
- VPN: Access through the Internet is available.
- Third Party Provider

## 2.4 Bandwidth Requirements

The minimum network connections that BOX accepts is 1Gigabit per second (gbps). Additional bandwidth may be required to receive the HSVF, as shown in the following table:

**Table 2: HSVF Bandwidth Requirements**

HSVF	Required Bandwidth
L1 (top of book) and L2 (market depth) feeds	10 Gbps
1Gbps L1 (top of book), PIP, or Strategy feeds	1 Gbps

## 2.5 WAN IP Addressing

The network device peer addresses assigned to the Ethernet links that connect the client equipment to the BOX trading network will be assigned by BOX unless clients supply their own addresses.



## 2.6 Host IP Addressing

The client must provide the IP addresses of its hosts that will connect to the BOX networks. If possible, the clients should supply public IP addresses assigned to them by the IANA (Internet Assigned Numbers Authority). If public IP addresses are not available to the client, then the client may choose to use private (non-routable) addresses from the reserved IP address ranges as outlined in RFC1597 (Address Allocation for Private Internets) under the condition that the addresses do not conflict with any addresses currently used on the BOX networks.

## 2.7 IP Routing

Typically, IP routing will be done using either static routes or Border Gateway Protocol (BGP). Details are to be discussed with our technical network staff.

## 2.8 Network Security

The BOX trading networks and hosts are protected by the use of packet filtering and firewalls. Security measures in place are meant to protect the BOX trading networks and hosts from intentional or accidental access from client connections. These measures are in no way intended to provide security to the clients themselves. If clients feel they require additional security for their networks, they are encouraged to put in place the security measures deemed appropriate.

## Section 3 HSVF Multicast Specifications

### 3.1 HSVF Multicast

For each trading slice, the HSVF is offered in different instances so that Participants may choose the market data messages they wish to receive.

**Table 3: HSVF Multicast**

Description	Line Designation	HSVF Messages Included
Level 1 (best limit)	<b>s1</b> ( <b>s</b> specifies the trading slice)	Options: C, D, F, GC, GR, I, J, M, N, O, Q, T  Complex Order (Strategy): CS, FS, GS IS, JS, MS, NS, OS, QS, TS
Level 1 (best limit) 1Gbps	<b>s1</b> ( <b>s</b> specifies the trading slice)	Options: C, D, F, GC, GR, I, J, M, N, O, Q, T  Complex Order (Strategy): CS, FS, GS IS, JS, MS, NS, OS, QS, TS
Level 5 (5 limits)	<b>s5</b> ( <b>s</b> specifies the trading slice)	Options: C, D, GC, GR, H, I, J, M, N, O, Q, T  Complex Order (Strategy): CS, GS, HS, IS, JS, MS, NS, OS, QS, TS
PIP only	<b>sP</b> ( <b>s</b> specifies the trading slice)	Options: J, M, N, O, Q, T

		Complex Order (Strategy): JS, MS, NS, OS, QS, TS
Strategy only (with market depth)	sC (s specifies the trading slice)	Complex Order (Strategy): CS, GS, HS, IS, JS, MS, NS, OS, QS, TS

To ensure resiliency, two instances of the feed are available: “A” and “B” feeds. Both offer identical data and clients can choose to receive either or both.

### 3.2 Multicast Routing

The BOX multicast network uses PIM sparse mode (PIM-SM) exclusively. PIM dense mode (PIM-DM) and static Internet Group Management Protocol (IGMP) joins are not supported.

PIM-SM requires the use of a Rendezvous Point (RP) which client routers forward multicast join requests. Separate RPs are made available in the Secaucus and Chicago locations.

Each feed is sourced from an address range specific to its source location. For optimum multicast routing, clients are expected to support the creation of shortest path trees (SPT). This will ensure the lowest latency, most efficient reception of the feeds, and allow clients to control the redundant reception of both A and B feeds.

Optimal feed reception ultimately depends on the source tree determined from the client's router point of view. The location from which clients receive a feed will depend on the routes to the source address range contained within the client router's unicast routing table. Clients' unicast routing tables must be accurate in order to ensure they receive the feeds from their intended location.

To aid clients in obtaining the multicast feeds from the desired locations, appropriate routes will be advertised to the client routers via BGP (Border gateway Protocol). Clients must configure their network equipment to accept the desired routes from their preferred locations and determine the unicast routing table that will be used to create the source tree back to the feed sources. Please refer to [Connection Details](#) for route details.

### 3.3 Disaster Recovery

If BOX needs to operate from its Disaster Recovery (DR) site, the multicast feeds will only be available from the Chicago location.

### 3.4 Message Recovery (Retransmission)

Two options are available to clients to recover lost messages:

- Feed arbitration
- TCP retransmission

### 3.4.1 Feed Arbitration

Feed arbitration offers the quickest way to recover lost messages. Clients may read both “A” and “B” instances of the feed simultaneously. If a gap is experienced on one feed (and since both feeds disseminate identical data), the client’s application should be able to retrieve the missing message(s) from the other feed.

### 3.4.2 TCP Retransmission

Clients may connect to recovery servers and request the missing messages. This service is offered over TCP and is available in Secaucus and Chicago locations.

For redundancy, two recovery servers are provided at the location. Either server can be used to retrieve missing messages as the recovery systems are not tied to any particular feed. Since both the A and B feeds are identical, clients can connect to any recovery server to retrieve missing messages.

If a recovery server is not available (due to a technical issue), clients must connect to the alternate server to request message retransmission.

## 3.5 Test Access

To provide an environment in which Participants can test their applications, the BOX multicast services are also available from the BOX test environment, with some restrictions.

The purpose of the test environment is to perform functional testing. The test environment does not offer any performance testing capabilities.

### 3.5.1 VPN Limitations

Multicast distribution is not compatible with VPN technology making it impossible to send a multicast feed to clients connected via VPN.

### 3.5.2 Test Multicast Feeds

Two separate instances of the HSVF are offered:

- Test environment 1 (ISV-1) simulating 8 trading slices
- Test environment 2 (ISV-2) simulating 2 trading slices

The environment to be used by the client depends on its availability and BOX services being tested. The environment that the client should use will be specified by BOX MOC at the time a client makes arrangements to set up a test session.

### 3.5.3 Retransmission

Two instances of HSVF retransmission services are offered:

- Test environment 1 (ISV-1)
- Test environment 2 (ISV-2)

The environment to be used by the client will be determined by BOX MOC at the time the testing occurs.

Clients need to certify use of the retransmission services prior to obtaining access to production retransmission services.

Retransmission is available over VPN.

## **Section 4 Point of Presence (POP) Sites**

---

There are two (2) POP sites available to connect to the BOX production network.  
(Test access is only available from NY4)

### **4.1 Secaucus Site (Equinix NY4)**

The Secaucus site is located at:

BOX Options Exchange  
C/o Equinix  
755 Secaucus Road  
Secaucus, NJ, 07094  
NPA-NXX: 201-864  
Support 1 gigabit and 10 gigabit connections

### **4.2 Chicago Site (Equinix CH1)**

The Chicago site is located at:

BOX Options Exchange  
C/o Equinix  
350 East Cermak Road, 6th Floor Ste 650  
Chicago, IL, 60616  
NPA-NXX: 312-225  
Support 1 gigabit and 10 gigabit connections

## Appendix A Connection Details

---

This appendix describes the connection details for both the test and production networks.

### A.1 VPN Connections

VPN access is available to the BOX test environment only. Typically, VPN connections are setup in tunnel mode between the client's VPN device and the BOX VPN routers. Over the VPN connection, traffic will be routed between the client's internal hosts and the BOX test hosts. To initiate a VPN connection, the client must have a fixed, internet reachable IP address to be able to pass through BOX's firewalls. For VPN connections, the ISAKMP policies listed in Table 4 are accepted.

**Table 4: VPN Connections Policies**

Policy 1	
Encryption:	Advanced Encryption Standard (AES) [128 / 192 / 256 bits]
Hash:	SHA [256 / 384 / 512]
Authentication:	Pre-shared key
Diffie-Hellman group:	Group 14 and above (minimum 2048 bit)
Lifetime:	7200 seconds
Policy 2	
Encryption:	Advanced Encryption Standard (AES) [128 / 192 / 256 bits]
Hash:	SHA [256 / 384 / 512]
Authentication:	Pre-shared key
Diffie-Hellman group:	Group 14 and above (minimum 2048 bit)
Lifetime:	7200 seconds

## **A.2 Production Connections**

For production connections, the client is responsible for ordering the appropriate telecommunications lines and/or cross connects to BOX data cabinets.

## **A.3 Setting-up Connections to Secaucus Site (Equinix NY4)**

Clients can order a cross connect to BOX:

- BOX cage # 08765 Cabinet # 0000 for Equinix NY4
- Deliver to next available patch panel port

When Equinix completes the cross connects, they will provide the client with cross connect details (cable ID, patch panel port, etc). BOX needs this information in order to complete the connection. There are several choices for cross connects:

- Single mode fiber
- Multi-mode fiber
  - For multi-mode, the fiber size is important (50 micron or 62.5 micron)

BOX supports both models but needs to know which one in order to match the patch cord.

## **A.4 Setting-up Connections to Chicago Site (Equinix CH1)**

Clients already present at Equinix CH1 can order a cross connect to BOX:

- BOX cage # 950 for Equinix CH1 Cabinet #0000
- Deliver to next available patch panel port

When Equinix completes the cross connects, they will provide the client with cross connect details (cable ID, patch panel port, etc). BOX needs this information in order to complete the connection. There are several choices for cross connects:

- Single mode fiber
- Multi-mode fiber
  - For multi-mode, the fiber size is important (50 micron or 62.5 micron)

BOX supports both models but needs to know which one in order to match the patch cord.



## Appendix B Multicast Feed Details

---

### B.1 Secaucus Production

#### Rendezvous Point (RP)

Table 5: (RP) – Secaucus

Description	Address
Secaucus production RP	198.235.27.223

#### Multicast Sources

Table 6: Multicast Sources – Secaucus

Feed	Source Address Range
Secaucus “A” feeds	198.235.27.40/29
Secaucus “B” feeds	198.235.27.48/29

#### IP Routing

Table 7 details the IP routing information that BOX will advertise to clients. Clients can then adjust their routing in order to determine the connection over which to receive the desired feed.

Table 7: IP Routing – Secaucus

Description	Advertised Route
Default BOX services route	198.235.27.0/24
Secaucus production RP	198.235.27.223/32
Secaucus production “A” feeds	198.235.27.40/29
	198.235.27.40/32
	198.235.27.41/32

Description	Advertised Route
Secaucus production “B” feeds	198.235.27.48/29
	198.235.27.48/32
	198.235.27.49/32

## Multicast Lines

The following table provides details to the multicast lines that will be available from the Secaucus location.

**Table 8: Multicast Lines – Secaucus**

Secaucus POP					
Line	Description	“A” Feed Multicast Group Addresses	UDP Port	“B” Feed Multicast Group Addresses	UDP Port
11	Best Limit	224.0.124.1	21401	224.0.124.49	21404
21	Best Limit	224.0.124.2	22401	224.0.124.50	22404
31	Best Limit	224.0.124.3	23401	224.0.124.51	23404
41	Best Limit	224.0.124.4	24401	224.0.124.52	24404
51	Best Limit	224.0.124.5	25401	224.0.124.53	25404
61	Best Limit	224.0.124.6	26401	224.0.124.54	26404
71	Best Limit	224.0.124.7	27401	224.0.124.55	27404
11	Best Limit <b>1Gbps</b>	224.0.124.192	21421	224.0.124.200	21424
21	Best Limit <b>1Gbps</b>	224.0.124.193	22421	224.0.124.201	22424
31	Best Limit <b>1Gbps</b>	224.0.124.194	23421	224.0.124.202	23424
41	Best Limit <b>1Gbps</b>	224.0.124.195	24421	224.0.124.203	24424
51	Best Limit <b>1Gbps</b>	224.0.124.196	25421	224.0.124.204	25424

Secaucus POP					
Line	Description	“A” Feed Multicast Group Addresses	UDP Port	“B” Feed Multicast Group Addresses	UDP Port
61	Best Limit <b>1Gbps</b>	224.0.124.197	26421	224.0.124.205	26424
71	Best Limit <b>1Gbps</b>	224.0.124.198	27421	224.0.124.206	27424
81	Best Limit <b>1Gbps</b>	224.0.124.199	28421	224.0.124.207	28424
15	5 Limits	224.0.124.9	21402	224.0.124.57	21405
25	5 Limits	224.0.124.10	22402	224.0.124.58	22405
35	5 Limits	224.0.124.11	23402	224.0.124.59	23405
45	5 Limits	224.0.124.12	24402	224.0.124.60	24405
55	5 Limits	224.0.124.13	25402	224.0.124.61	25405
65	5 Limits	224.0.124.14	26402	224.0.124.62	26405
75	5 Limits	224.0.124.15	27402	224.0.124.63	27405
85	5 Limits	224.0.124.16	28402	224.0.124.64	28405
1P	PIP only	224.0.124.17	21403	224.0.124.65	21406
2P	PIP only	224.0.124.18	22403	224.0.124.66	22406
3P	PIP only	224.0.124.19	23403	224.0.124.67	23406
4P	PIP only	224.0.124.20	24403	224.0.124.68	24406
5P	PIP only	224.0.124.21	25403	224.0.124.69	25406
6P	PIP only	224.0.124.22	26403	224.0.124.70	26406
7P	PIP only	224.0.124.23	27403	224.0.124.71	27406
8P	PIP only	224.0.124.24	28403	224.0.124.72	28406
1C	Strategy only	224.0.124.25	21407	224.0.124.73	21408

Secaucus POP					
Line	Description	“A” Feed Multicast Group Addresses	UDP Port	“B” Feed Multicast Group Addresses	UDP Port
2C	Strategy only	224.0.124.26	22407	224.0.124.74	22408
3C	Strategy only	224.0.124.27	23407	224.0.124.75	23408
4C	Strategy only	224.0.124.28	24407	224.0.124.76	24408
5C	Strategy only	224.0.124.29	25407	224.0.124.77	25408
6C	Strategy only	224.0.124.30	26407	224.0.124.78	26408
7C	Strategy only	224.0.124.31	27407	224.0.124.79	27408
8C	Strategy only	224.0.124.32	28407	224.0.124.80	28408

## Line to Source Mapping

The following table provides the source host IP to line mapping.

**Table 9: Multicast line to source IP - Secaucus**

Secaucus POP					
Best Limit Lines	5 Limit Lines	PIP Lines	Strategy Lines	"A" Feed Sources	"B" Feed Sources
11	15	1P	1C	198.235.27.41	198.235.27.49
21	25	2P	2C	198.235.27.41	198.235.27.49
31	35	3P	3C	198.235.27.41	198.235.27.49
41	45	4P	4C	198.235.27.40	198.235.27.48
51	55	5P	5C	198.235.27.40	198.235.27.48
61	65	6P	6C	198.235.27.40	198.235.27.48
71	75	7P	7C	198.235.27.40	198.235.27.48
81	85	8P	8C	198.235.27.40	198.235.27.48
11 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48
21 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48
31 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48
41 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48
51 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48
61 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48
71 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48
81 (1Gbps)	n/a	n/a	n/a	198.235.27.40	198.235.27.48

## Retransmission

**Table 10: Retransmission Feeds – Secaucus**

Feeds	Secaucus Retransmission Server 1	Secaucus Retransmission Server 2	TCP Port
Trading slice 1 (11, 15, 1P, 1C)	198.235.27.47	198.235.27.55	21410

Feeds	Secaucus Retransmission Server 1	Secaucus Retransmission Server 2	TCP Port
Trading slice 2 (21, 25, 2P, 2C)	198.235.27.47	198.235.27.55	22410
Trading slice 3 (31, 35, 3P, 3C)	198.235.27.47	198.235.27.55	23410
Trading slice 4 (41, 45, 4P, 4C)	198.235.27.47	198.235.27.55	24410
Trading slice 5 (51, 55, 5P, 5C)	198.235.27.47	198.235.27.55	25410
Trading slice 6 (61, 65, 6P, 6C)	198.235.27.47	198.235.27.55	26410
Trading slice 7 (71, 75, 7P, 7C)	198.235.27.47	198.235.27.55	27410
Trading slice 8 (81, 85, 8P, 8C)	198.235.27.47	198.235.27.55	28410

## B.2 Chicago DR

This information applies to the Chicago site.

### Rendezvous Point

Table 11: RP – Chicago

Description	Address
Chicago production RP	198.235.27.222

### Multicast Sources

Table 12: Multicast Sources – Chicago

Feed	Source Address Range
Chicago "A" feeds	198.235.27.232/29
Chicago "B" feeds	198.235.27.240/29

## IP Routing

Table 13 details the IP routing information that BOX will advertise to clients. Clients can then adjust their routing in order to determine over which of their connections they will receive the desired feed.

**Table 13: IP Routing – Chicago**

Description	Advertised Route
Default BOX services route	198.235.27.0/24
Chicago production RP	198.235.27.222/32
Chicago production “A” feeds	198.235.27.232/29
Chicago production “B” feeds	198.235.27.240/29

## Multicast Lines

Table 14 lists the multicast groups that will be available from the Chicago location.

**Table 14: Multicast Lines – Chicago**

Chicago POP					
Line	Description	“A” Feed Multicast Group Addresses	UDP Port	“B” Feed Multicast Group Addresses	UDP Port
11	Best Limit	224.0.124.97	21401	224.0.124.145	21404
21	Best Limit	224.0.124.98	22401	224.0.124.146	22404
31	Best Limit	224.0.124.99	23401	224.0.124.147	23404
41	Best Limit	224.0.124.100	24401	224.0.124.148	24404
51	Best Limit	224.0.124.101	25401	224.0.124.149	25404
61	Best Limit	224.0.124.102	26401	224.0.124.150	26404
71	Best Limit	224.0.124.103	27401	224.0.124.151	27404
81	Best Limit	224.0.124.104	28401	224.0.124.152	28404
11	Best Limit <b>1Gbps</b>	224.0.124.208	21421	224.0.124.216	21424

Chicago POP					
Line	Description	“A” Feed Multicast Group Addresses	UDP Port	“B” Feed Multicast Group Addresses	UDP Port
21	Best Limit <b>1Gbps</b>	224.0.124.209	22421	224.0.124.217	22424
31	Best Limit <b>1Gbps</b>	224.0.124.210	23421	224.0.124.218	23424
41	Best Limit <b>1Gbps</b>	224.0.124.211	24421	224.0.124.219	24424
51	Best Limit <b>1Gbps</b>	224.0.124.212	25421	224.0.124.220	25424
61	Best Limit <b>1Gbps</b>	224.0.124.213	26421	224.0.124.221	26424
71	Best Limit <b>1Gbps</b>	224.0.124.214	27421	224.0.124.222	27424
81	Best Limit <b>1Gbps</b>	224.0.124.215	28421	224.0.124.223	28424
15	5 Limits	224.0.124.105	21402	224.0.124.153	21405
25	5 Limits	224.0.124.106	22402	224.0.124.154	22405
35	5 Limits	224.0.124.107	23402	224.0.124.155	23405
45	5 Limits	224.0.124.108	24402	224.0.124.156	24405
55	5 Limits	224.0.124.109	25402	224.0.124.157	25405
65	5 Limits	224.0.124.110	26402	224.0.124.158	26405
75	5 Limits	224.0.124.111	27402	224.0.124.159	27405
85	5 Limits	224.0.124.112	28402	224.0.124.160	28405
1P	PIP only	224.0.124.113	21403	224.0.124.161	21406
2P	PIP only	224.0.124.114	22403	224.0.124.162	22406
3P	PIP only	224.0.124.115	23403	224.0.124.163	23406
4P	PIP only	224.0.124.116	24403	224.0.124.164	24406



Chicago POP					
Line	Description	“A” Feed Multicast Group Addresses	UDP Port	“B” Feed Multicast Group Addresses	UDP Port
5P	PIP only	224.0.124.117	25403	224.0.124.165	25406
6P	PIP only	224.0.124.118	26403	224.0.124.166	26406
7P	PIP only	224.0.124.119	27403	224.0.124.167	27406
8P	PIP only	224.0.124.120	28403	224.0.124.168	28406
1C	Strategy only	224.0.124.121	21407	224.0.124.169	21408
2C	Strategy only	224.0.124.122	22407	224.0.124.170	22408
3C	Strategy only	224.0.124.123	23407	224.0.124.171	23408
4C	Strategy only	224.0.124.124	24407	224.0.124.172	24408
5C	Strategy only	224.0.124.125	25407	224.0.124.173	25408
6C	Strategy only	224.0.124.126	26407	224.0.124.174	26408
7C	Strategy only	224.0.124.127	27407	224.0.124.175	27408
8C	Strategy only	224.0.124.128	28407	224.0.124.176	28408

## Retransmission

Table 15: Retransmission Feeds – Chicago

Feeds	Chicago Retransmission Server 1	Chicago Retransmission Server 2	TCP Port
Trading slice 1 (11, 15, 1P, 1C)	198.235.27.239	198.235.27.247	21410
Trading slice 2 (21,25, 2P, 2C)	198.235.27.239	198.235.27.247	22410
Trading slice 3 (31, 35, 3P, 3C)	198.235.27.239	198.235.27.247	23410
Trading slice 4 (41, 45, 4P, 4C)	198.235.27.239	198.235.27.247	24410

Feeds	Chicago Retransmission Server 1	Chicago Retransmission Server 2	TCP Port
Trading slice 5 (51, 55, 5P, 5C)	198.235.27.239	198.235.27.247	25410
Trading slice 6 (61, 65, 6P, 6C)	198.235.27.239	198.235.27.247	26410
Trading slice 7 (71, 75, 7P, 7C)	198.235.27.239	198.235.27.247	27410
Trading slice 8 (81, 85, 8P, 8C)	198.235.27.239	198.235.27.247	28410

### B.3 Test Environment

As described in [Section 3](#) of this document, test multicast services are available in the Test environment.

#### Rendezvous Point

Table 16: RP – Test Environment

Description	Address
Test environment RP	198.235.30.26

#### Multicast Sources

Table 17: Multicast Sources – Test Environment

Feed	Source Address Range
ISV 1 feeds	198.235.30.48/32
ISV 2 feeds	198.235.30.49/32

## IP Routing

The following table details the IP routing information that BOX will advertise via the test environment.

**Table 18: IP Routing – Test Environment**

Description	Advertised Route
Default BOX services route	198.235.30.0/24
Test RP	198.235.30.26/32
Test ISV 1 feeds	198.235.30.48/32
Test ISV 2 feeds	198.235.30.49/32

## Multicast Lines

Table 20 lists the multicast group addresses for the ISV 1 and ISV 2 test feeds. These feeds are broadcasted from the test environment.

**Table 19: Multicast Lines – Test Environment**

Line	Description	ISV 1 Multicast Groups	UDP Port	ISV 2 Multicast Groups	UDP Port	
11	Best Limit	224.0.186.1	11401	224.0.186.49	11404	
21	Best Limit	224.0.186.2	12401	224.0.186.50	12404	
31	Best Limit	224.0.186.3	13401	224.0.186.51	13404	Reserved for future use
41	Best Limit	224.0.186.4	14401	224.0.186.52	14404	
51	Best Limit	224.0.186.5	15401	224.0.186.53	15404	
61	Best Limit	224.0.186.6	16401	224.0.186.54	16404	
71	Best Limit	224.0.186.7	17401	224.0.186.55	17404	
81	Best Limit	224.0.186.8	18401	224.0.186.56	18404	
15	5 Limits	224.0.186.9	11402	224.0.186.57	11405	
25	5 Limits	224.0.186.10	12402	224.0.186.58	12405	
35	5 Limits	224.0.186.11	13402	224.0.186.59	13405	Reserved for future use
45	5 Limits	224.0.186.12	14402	224.0.186.60	14405	
55	5 Limits	224.0.186.13	15402	224.0.186.61	15405	
65	5 Limits	224.0.186.14	16402	224.0.186.62	16405	
75	5 Limits	224.0.186.15	17402	224.0.186.63	17405	
85	5 Limits	224.0.186.16	18402	224.0.186.64	18405	
1P	PIP only	224.0.186.17	11403	224.0.186.65	11406	
2P	PIP only	224.0.186.18	12403	224.0.186.66	12406	
3P	PIP only	224.0.186.19	13403	224.0.186.67	13406	
4P	PIP only	224.0.186.20	14403	224.0.186.68	14406	

Line	Description	ISV 1 Multicast Groups	UDP Port	ISV 2 Multicast Groups	UDP Port	
5P	PIP only	224.0.186.21	15403	224.0.186.69	15406	Reserved for future use
6P	PIP only	224.0.186.22	16403	224.0.186.70	16406	
7P	PIP only	224.0.186.23	17403	224.0.186.71	17406	
8P	PIP only	224.0.186.24	18403	224.0.186.72	18406	
1C	Strategy only	224.0.186.25	11407	224.0.186.73	11408	
2C	Strategy only	224.0.186.26	12407	224.0.186.74	12408	
3C	Strategy only	224.0.186.27	13407	224.0.186.75	13408	Reserved for future use
4C	Strategy only	224.0.186.28	14407	224.0.186.76	14408	
5C	Strategy only	224.0.186.29	15407	224.0.186.77	15408	
6C	Strategy only	224.0.186.30	16407	224.0.186.78	16408	
7C	Strategy only	224.0.186.31	17407	224.0.186.79	17408	
8C	Strategy only	224.0.186.32	18407	224.0.186.80	18408	

## Retransmission

Test retransmission services are offered from the test environment only.

**Table 20: Retransmission Feeds – Test Environment**

Feeds	ISV 1 Retransmission Server	ISV 1 TCP Port	ISV 2 Retransmission Server	ISV 2 TCP Port	
Trading slice 1 (11, 15, 1P, 1C)	198.235.30.19	21410	198.235.30.20	11410	
Trading slice 2 (21, 25, 2P, 2C)	198.235.30.19	22410	198.235.30.20	12410	
Trading slice 3 (31, 35, 3P, 3C)	198.235.30.19	23410	198.235.30.20	13410	Reserved for future use
Trading slice 4 (41, 45, 4P, 4C)	198.235.30.19	24410	198.235.30.20	14410	
Trading slice 5 (51, 55, 5P, 5C)	198.235.30.19	25410	198.235.30.20	15410	
Trading slice 6 (61, 65, 6P, 6C)	198.235.30.19	26410	198.235.30.20	16410	
Trading slice 7 (71, 75, 7P, 7C)	198.235.30.19	27410	198.235.30.20	17410	
Trading slice 8 (81, 85, 8P, 8C)	198.235.30.19	28410	198.235.30.20	18410	



**BOX**<sup>SM</sup>  
TECHNOLOGY

---

**BOX Technology.**

2000 Mansfield St Suite 510,  
Montreal, Quebec, H3A 2Z6  
Canada